



Professional Compact Colour LED All-in-One Printer

with efficiency and connectivity built-in

MFC-L8390CDW



www.brother.ae

Professional Compact Colour LED All-in-One Printer

Ideal for businesses needing a professional, compact colour multifunctional device.

The user-friendly MFC-L8390CDW, quietly delivers high-quality documents without compromising on speed. Making this efficient device the perfect partner for your busy office.

MFC-L8390CDW



Key features:

- Print up to 30 pages per minute
- 2-Sided print, up to 12 sides per minute
- 2-Sided scan, up to 56 images per minute³
- 8.76cm Colour touchscreen
- Gigabit ethernet, 2.4GHz WiFi and USB
- Print or scan directly from desktop, USB or mobile app
- 512MB Internal memory
- 50 Sheet 2-Sided Automatic Document Feeder (ADF),
 250 Sheet paper input tray expandable up to 250 sheets¹¹
- Comes with 1,000 black, 1,000 colour page yield toners, 4,500 black, 4,000 colour maximum yield available⁷
- Compatible with Brother and 3rd Party solutions¹⁹
- NFC for secure authentication

Quiet without compromise

With its streamlined design, the MFC-L8390CDW is engineered to print quietly whilst delivering speeds up to 25% faster than the previous generation. So you can print continuously without distraction and focus on your business.

Compact and expertly engineered Designed by experts, our most compact, professional colour multifunction printer delivers high-quality outputs every time, allowing you to make the most of your office space. Every component has been optimised to reduce the overall size of the device without compromising on performance.

With easy paper access, the MFC-L8390CDW has been developed for high print volume to meet the needs of a busy office.

Flexibility that saves time

The MFC-L8390CDW has been designed to seamlessly fit into your office space, whilst meeting the specific print requirements of your business. By adding an optional paper tray, it gives you the flexibility to increase the amount your business can print from the one device.

Solutions ready

Automate workflows and improve business processes and security with print management solutions. We offer a suite of document management, security and workflow solutions which can be added to the MFC-L8390CDW to provide additional professional features to further improve your business processes.

Seamless integration

As a Brother customer, you will have access to a wide choice of leading software vendors including Kofax, YSoft, FollowMe and many more.

We work closely with our software partners across print management and document capture to create tailored solutions for your specific requirements. When we partner with a software vendor, we ensure your MFC-L8390CDW works even harder to meet your needs.



Make printing simple with Brother MPS Managed print services (MPS) supports you to get the best out of your devices. That's why the MFC-L8390CDW has been designed with MPS in mind.

Whatever your printing needs, we'll be "At your side" to find the solution that simplifies printer admin, saves time, keeps costs down, and helps you stay productive, with:

- No long-term commitments
- Ink and toner delivery before you run out
- Quick breakdown support
- Easy supplies recycling



Secure by design

To keep pace with the ever-evolving legislation on privacy and data security, our devices offer the latest industry-standard security features to securely protect your data.

All our products are secure as standard. With businesses shifting towards Zero Trust environments, we know that security is your highest priority. Our security experts continuously research new enhancements to products, solutions and services to proactively ensure all our products are 'secure by design'.

The MFC-L8390CDW provides a range of robust features. It uses triple-layer security at a device, network and document level which is verified through external security certification. This offers added peace of mind and guarantees that the integrity of your data is maintained at every step

The MFC-L8390CDW comes with a flexible suite of security features and solutions that can be tailored to your business, enabling you to easily audit, control and manage your fleet of devices securely.





Your device protects your business by reducing its attack surface through:

Restricting user access - by using LDAPS, Windows Active Directory together with NFC authentication, only authorised users are able to access the device.

Restricting privileges at a device level - with Secure Function Lock and Setting Lock, only authorised users are permitted access to specific functions.

Maintaining device integrity - with runtime intrusion detection, Secure Boot, digitally signed firmware and end-to-end encrypted connections, devices are always performing at their optimum level of security.







Intrusion protection - with protocol management, interface restrictions and IPV4 filtering, you have the flexibility to adapt device settings to your business.

Secure connection - securely connect to enterprise level wired and wireless networks through industry standard IEEE 802.1X.

Secure encrypted communication - by using flexible industry standards such as TLS, SSH, IPSEC, HTTPS and SNMP3, your business can tailor the device to its network.

Easily manage and configure your security profile - using Device Master Settings, BRAdmin Pro 4 and Mass Deployment Tool, your business can apply settings to entire fleets of devices.

Audit your devices - using SIEM integration through Syslog, you can gather real time usage information on your devices.



Your documents are protected through encryption, storage protection and secure print solutions including:

Encrypted document transfer - when you send your print data from your computer to the device, IPPS/HTTPS encryption ensures your data is secure and unreadable.

Secure scan data transfer - whether you are scanning to your local network or over the internet via Web Connect or a cloud-based service, your data is protected using TLS, HTTPS, SFTP (SSH).

Non-persistent internal memory - all print job data is automatically wiped during a reboot and data is purged, ensuring no information is left on the device. **Secure print release -** using a Brother secure print solution, documents are only released when you are ready to print and collect them.

3rd party integration - through Brother Solutions Interface (BSI), our devices can be fully integrated with trusted 3rd party partners such as Kofax and YSoft, which adds an extra layer of security to your business.





Technology Electrophotographic LED

Memory 512MB

Control panel 8.76cm Colour Touchscreen LCD Local Interface Hi-Speed USB 2.0, USB 2.0 Host (Front)

Wired Network Gigabit Ethernet

Wireless Network 2.4GHz Support

Carton Contents Device, Inbox Toners, Drum Unit, Power Supply Cord, Quick Set-Up Guide

Print

Print Speed (A4) 1-Sided: 30ppm Mono/Colour 2-Sided: 12 sides per minute Mono/Colour

FPOT (First Print Out Time) Up to 12.5 Seconds Mono/Colour

Quiet Mode A mode to reduce the printing noise **Resolution** Up to 600 x 600dpi

Print Languages PCL5e, PCL5c, PCL6 (PCL XL Class 3.0), BR-Script3, PDF Version 1.7

Embedded Fonts (PCL) 73 scalable fonts, 12 bitmap fonts

Embedded Barcodes (PCL)

16 bar codes* *Code39, Interleaved 2 of 5, FIM (US-PostNet), Post Net (US-PostNet) EAN-8, EAN-13, UPC-A, UPC-E, Codabar, ISBN (EAN), ISBN (UPC-E), Code128 (set A, set B, set C), EAN128 (set A, set B, set C), Code93, GS1Databar, MSI

Embedded Fonts (Postscript)

66 scalable fonts

Printer Functions

N-up Printing Reduce pages into a single page layout

Poster Printing Enlarge a single page into a poster using 2x2, 3x3, 4x4 or 5x5 pages

Watermark Printing Watermark your documents

with predefined text, custom logo or custom messages

Direct Print

Print directly from a USB flash memory drive. Supported formats include: PDF version 1.7, JPEG, Exif+JPEG, PRN (created by own printer driver), TIFF (scanned by Brother model)

Manual 2-Sided Print

Manual 2-sided printing (recommended for media not supported by automatic 2-sided print)

Carbon Copy

Prints additional copies of the same document to paper taken from additional paper trays

Print Complete Notice

A printing notification can be set to go to your computer

Secure Print

Protect print jobs with a 4 digit release code required at the device in order for them to be printed

Universal Print (Microsoft 365)

Print effortlessly with native Universal Print support on Brother printers Printer **Driver**

Windows

Windows 11 (32 and 64 bit editions) and more

macOS

Printing via macOS requires the use of AirPrint. Mac drivers are not provided.

Linux CUPS, LPD/LPRng (x86/x64 environment)

ChromeOS

Supports native ChromeOS printing **PCL Driver** PCL6 (Standard)

Universal Printer Driver

Driver for Windows that enables you to print to any network or locally connected Brother printer

Visit support.brother.com for the full list of supported OS and to download the latest drivers and software.

Paper Handling¹¹

Paper Input Standard Tray 250 Sheets

Multi Purpose Tray

30 Sheets

Automatic Document Feeder (ADF) 50 Sheets

Paper Output 150 sheets A4

Envelope Printing

Yes from multi purpose tray

Media Sizes Standard Tray

A4, Letter, Legal, Mexico Legal, India Legal, Executive, A5, A5 Long Edge, A6, B5 (JIS), B5 (ISO), B6 (JIS), A4 Short (270mm), Folio, 16K (195 x 270mm)

Optional Tray

A4, Letter, B5 (JIS), A5, Executive, Legal, Mexico Legal, India Legal, A4 Short (270mm Paper), Folio, 16K (195 x 270mm) Paper, Recycled Paper, Bond,

Multi Purpose Tray Width 76.2 to 216 mm Length 116 to 355.6 mm Envelope: COM-10, DL, C5, Monarch

ADF

Width: 105 to 215.9 mm, Length: 147.3 to 355.6 mm

Scanner Glass Up to A4/Letter

Auto 2-Sided

Α4

Media Type and Weights Standard Tray

Plain Paper, Thin Paper, Thick Paper, Recycled Paper 60-163qsm

Optional Tray

Plain Paper, Thin Paper, **Recycled Paper** 60 to 105gsm

Multi Purpose Tray

Plain Paper, Thin Paper, Thick Label, Envelope, Env. Thin, Env. Thick, Glossy Paper 60-163gsm

ADF

Plain, Thin paper and Recycled paper 64-105gsm

Auto 2-Sided

Plain Paper, Thin Paper, **Recycled Paper** 64-105qsm

Mobile and Web Connectivity

Brother Mobile Connect¹⁷ (Android)

Print from, scan to, preview copies and check the machine status from an Android device

Brother Mobile Connect¹⁷ (iPad / iPhone)

Print from, scan to, preview copies and check the machine status from an iPad / iPhone

Apple AirPrint¹⁷

Print from and scan to most common file types from any AirPrint enabled application

Brother Print Service Plugin¹⁷

Print from an Android device without a dedicated App.

Mopria^{™ 17}

Print most common file types from Mopria[™] supported Android devices

Brother Apps¹⁸

Scan to Mobile, Scan to Searchable PDF, Fax forward to Cloud/E-mail, Scan to PowerPoint, Scan to Excel, Scan to Word, Easy scan to E-mail

Web Connect¹⁸

Print from and scan to without using a PC on Box, Dropbox, Evernote, OneDrive, Google Drive[™] OneNote

Copy

Copy Speed (A4) 1-Sided: 30ppm Mono/Colour 2-Sided: Yes

Resolution Up to 600 x 600dpi FCOT (First Copy Out Time) Up to 13.5 Seconds Mono/Colour

Grey Scale 256 shades of grey (8 bit for each colour)

Copy Functions Multi-Copying/Stack/Sort Makes up to 999 copies of each

page / Stacks or Sorts
Enlargement/Reduction
Ratio

Reduce or Increase document sizes from 25% to 400% in 1% increments

N in 1 Copying

Allows the user to compress multiple pages on to a single A4 sheet

Scan

Scanner Type Dual CIS (Contact Image Sensor)

Colour and Mono Scanning Yes

Scan Speed (A4)³ 1-Sided: 27ipm Mono and 21ipm Colour 2-Sided: 56ipm Mono and 32ipm Colour Scan Resolution from ADF 600 x 600dpi

Scan Resolution from Scanner Glass 1200 x 1200dpi

Interpolated Scan Resolution Brother Scanner Utility enhances up to 19,200 x 19,200 dpi

Colour Depth

48 bit colour Processing (Input)24 bit colour Processing (Output)

Grey Scale

16 bit colour Processing (Input)8 bit colour Processing (Output)

Scanner Functions **Supported File Formats** Including PDF (PDF/A, Secure PDF, Signed PDF, Searchable¹⁷) JPEG, TIFF, XPS

Standard Functions¹⁷ Scan to USB, E-mail, OCR, Image and File

Network Scanning Scan to network folder (SMB)¹⁶, FTP, SFTP, Email Server, SharePoint (On Premise) Direct Scan

Scan directly to a USB flash memory storage

Scan Profile¹⁵

Create up to 25 preset network, SFTP/FTP profiles for an easy way to store multiple scan settings

Document Separation

Create scanned files based on blank sheet separation or a specific number of single sided images or sheets of paper, even if more documents are set on the ADF Scanner Drivers Windows TWAIN and WIA Windows 10 (32 and 64 bit editions)

macOS

Scanning via macOS requires the use of AirPrint. Mac drivers are not provided.

Visit support.brother.com for the full list of supported OS and to download the latest drivers and software.

Linux

SANE (32 and 64 bit editions)

ChromeOS

Supports native ChromeOS scanning

Fax

Automatic 2-Sided Faxing Yes

Fax Modem 33,600bps (Super G3)

Grey Scale 256 shades (8 bit) of grey are

available for faxing

Out of Paper Reception Up to 500 pages (ITU-T Test Chart, Standard Resolution, JBIG)

Broadcasting Send the same fax message up to 350 locations

Memory Transmission

Up to 500 pages (ITU-T Test Chart, Standard Resolution, JBIG)

Fax Functions

Internet Fax (I-Fax)

Fax documents over the internet as an email attachment

Fax to Server

Scan a document and send it over the network to a separate fax server

Automatic Redial

Automatic redialling if the recipient fax is busy

Telephone Index

An electronic, alphabetical listing of stored speed dials and group numbers

Chain Dialling

Allows the user to store parts for long dialing sequences in different speed dial locations

Batch Transmission

Stores documents for the same location in the machines memory for transmission in a single call

Fax Forwarding

Sends a fax received in memory to another pre-programmed fax number

Remote Retrieval

Allows users to remotely access their machine and retrieve stored fax messages

Fax Stamp

Add the date and time to all received faxes

Cover Page

Create custom cover pages for outgoing faxes

Station ID

An ID and fax number will be printed as the header of every fax sent

PC-Fax Send^{15,18} and Receive^{16,18}

Send and Receive faxes directly from your PC. Supports mono only

Distinctive Ring Detection

An external service that allows two or more telephone numbers shared on a single fixed line and use different ring tones (UK and Denmark only)

Error Correction Mode (ECM)

Detect line errors during fax transmission and resend the page(s) of the document that had an error (recipient machines must share this feature for it to work)

Auto Reduction

When receiving a single page document longer than A4 (297mm) the fax machine will automatically reduce the message to fit onto a single A4 sheet

Fleet Management Tools

BRAdmin Pro^{16,17} LAN/WAN management software

Driver Deployment Wizard^{16,17}

Easily create print drivers for hassle free deployment over your network

Status Monitor¹⁶

Monitor the status of your machine from your computer

Software

Brother iPrint&Scan Desktop^{15,17}

Print from, scan to, preview copies and check the machine status from Windows or macOS PC

PaperPort SE 14^{16,17}

Document management and sharing program from KOFAX

Utilities

Provides setup guides, manual, FAQ, troubleshooting and contact to Brother customer service

Connectivity

Wired Network Gigabit Ethernet (10Base-T/100Base-TX/1000Base-T)

Wireless Network 2.4GHz: IEEE 802.11 b/g/n (Infrastructure Mode) IEEE 802.11 g/n (Wi-Fi Direct)

Wi-Fi Direct®

Print wirelessly without having to go through a wireless access point (both automatic and manual methods supported)

Wireless Setup Support Wi-Fi Protected Setup (WPS)

Wireless Applications Vertical Pairing

Mobile

Print or scan from your mobile device with Brother Mobile Connect, Airprint, Mopria

Local Interface

Hi-Speed USB 2.0, USB 2.0 Host (Front)

Security Features

Wired Network Security

APOP, SMTP-AUTH, SSL/TLS (IPP, HTTP, SMTP, POP3, IMAP4, FTP), SNMP v3, 802.1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP-TTLS), Kerberos, IPsec

Wireless Network Security

WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (TKIP/AES), WPA3-SAE (AES) *Wi-Fi Direct supports WPA2-PSK (AES) only.

APOP, SMTP-AUTH, SSL/TLS (IPP, HTTP, FTP, SMTP, POP3, IMAP4), SNMP v3, 802.1x (EAP-FAST, PEAP, EAP-TLS, EAP-TTLS), Kerberos, IPsec

IPv4

ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/ Port9100, POP3, SMTP Client, IPP/IPPS, FTP Client and Server, CIFS Client, TELNET Server, SNMPv1/v2c/v3, HTTP/HTTPS server, TFTP client and server, ICMP, Web Services (Print/ Scan), SNTP Client, LDAPS, IMAP4, Syslog

IPv6

NDP, RA, DNS resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, IPP/IPPS, POP3, SMTP Client, FTP Client and Server, CIFS Client, TELNET Server, SNMPv1/v2c/v3, HTTP/HTTPS server, TFTP client and server, ICMPv6, SNTP Client, LDAPS, Web Services (Print/Scan), IMAP4, Syslog

Secure Print

Protect print jobs with a 4 digit release code required at the device in order for them to be printed

E-mail Notifications

Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing

E-mail Reports

Receive usage reports on a regular basis via e-mail

Setting Lock

Secures access to the devices control panel by locking it

Secure Function Lock 3.0

Use a 4 digit pin or a password to identify and authenticate an individual or groups of users over a network. Allows access control for up to 100 users

Syslog

Allows IT Admin to access a single application (SIEM tool) to get device status updates for audit purposes over Syslog

On-Premise Active Directory/LDAP Authentication

Utilise existing infrastructure to restrict access to Brother devices using AD/LDAP. Staff can easily use their existing network login credentials to authenticate

Restrict network protocols

The Protocol Control feature allows an administrator to restrict communication protocols (e.g. FTP, Telnet) as required

Store Print Log

Allows audit of a print log file saved to CIFS server. Record ID, type, name, user, date, time, page count for every print job

Near-Field Communications (NFC) / Card Reader Support

Integrated NFC Reader

Supported NFC standards include: (ISO14443 Type A) MIFARE Standard/Plus/ Ultralight/Ultralight C/DESfire my-d move, Tag-it (ISO15693 Type B)

Supplies and Consumables

Inbox Toner⁸ 1 x 1,000 pages (BK) 1 x 1,000 pages (CMY)

Standard Yield Toner⁸

TN279 1,500 pages (BK) 1,000 pages (CMY) High Yield Toner⁸ TN279XL 3,000 pages (BK) 2,300 pages (CMY)

Super High Yield Toner⁸ TN279XL 4,500 pages (BK) 4,000 pages (CMY) **Drum Unit**

DR279CL Approx. 30,000 pages at 3 pages per job

Belt Unit BU229CL Approx. 60,000 pages at 3 pages per job

Waste Toner Box

WT229CL Approx. 50,000 pages at 5 pages per job

Address Book

LDAP

The ability to connect to an external LDAP enabled address book, like Microsoft Exchange. Compatible with LDAP and LDAPS

Speed Dials

300 locations for E-mail addresses and fax numbers

Group Dial

A combination of up to 20 groups can be stored for broadcasting

3rd	Party	/
Cor	npati	bility

Brother Solutions Interface (BSI)

Create powerful cloud and on premise solutions directly integrating the advanced print, scan and security capabilities of Brother devices. For more information visit: www.brother.eu/developers

3rd Party Solutions

Compatible through Brother Solutions Interface (BSI) including Kofax ControlSuite, YSoft and more

Dimensions and Weights

With Carton (WxDxH) 497 x 583 x 533 mm - 25.7kg **Without Carton (WxDxH)** 410 x 462 x 401mm - 22.1kg

Duty Cycle

Recommended Monthly Up to 4,000 pages

Operating Requirement Power Requirement 220-240V AC 50/60Hz

Approx Power

Operating Environment Humidity 20 - 80 %

10°C - 32.5°C 50°F - 90.5°F

Storage Environment

Humidity 35 - 85 % 0°C - 40°C 32°F - 104°F

Environment

Consumption^{13,23} Copying: 620W Copying in quiet mode: 310W Printing: 620W Printing in quiet mode: 310W Ready: 70W Sleep: 10W Deep Sleep: 0.65W Power Off: 0.04W

TEC Value

0.48 kWh/week

Sound Power¹²

Printing: Mono 6.62B(A) Colour 6.67 B(A) Ready: Inaudible Quiet Mode: Mono 5.79B(A) Colour 5.86B(A) Deep Sleep: Inaudible

Sound Pressure¹²

PC Printing (Mono/Colour): Approx. 48 dB(A) Ready: Inaudible Quiet Mode: 43 dB(A)

- 3 Scan Speeds based on ISO/IEC 17991
- 8 Approx. declared yield value in accordance with ISO/IEC 19798
- 11 Capacity calculated with 80gsm paper
- 12 Sound pressure and sound power level in accordance with ISO 7779
- 13 Power consumption power off is measured according to IEC 62301 Edition 2.0
- 15 Windows and macOS only
- 16 Windows only
- 17 Optional download
- 18 Requires an Internet connection
- 19 Requires additional activation
- 23 Power consumption is measured using ENERGY STAR Ver 3.1 test method network configuration





Working with you for a better environment

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth. www.brotherearth.com All specifications correct at the time of printing and are subject to change. Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks of their respective companies.

> brother at your side